

PDRP-1001 Series Pre-Action/Deluge Control Panel



Models Available

- PDRP-1001 Pre-Action/Deluge Panel
- PDRP-1001E (International, 230V)
- PDRP-1001A (Canadian)

Optional Accessories Available

- 4XZM Zone Relay Module
- 4XTM Transmitter Module
- 4XLM LED Interface Module
- 4XMM Volt/Amp Meter
- RZA-4X Supervised Remote Annunciator
requires LED interface module (4XLM)
- NOTI•FIRE 911A Digital Communicator



Product Overview

- 2 initiating device circuits (Style B/D)**
- 2 notification appliance circuits (Style Y/Z)**
- 2 release circuits (Style Y)**
- Waterflow input (Style B/D)**
- Dual hazard option (combined or split release)**
- Supervisory input option (Style B/D)**
- Distinct audible indications for: 1 zone in alarm; 2 zones in alarm; release**
- Power-limited on all circuits except municipal box output**
- Alarm and trouble resound**
- Battery/earth fault supervision**
- Last event recall feature to trap intermittent trouble conditions**
- Fuse protection on all indicating/release circuits**
- Discharge timer: 0, 10, or 15 minutes**
- Disable/enable controls per initiating zone**
- Cross-zone option**

Features. Battery/earth fault supervision and fuse protection on all indicating/release circuits. Extensive transient protection. 6.5 AH to 15 AH battery options, up to 90 hours standby. Output circuits protected against false activations by 2-step command sequence and watchdog timer to supervise microprocessor. Last event recall feature to trap intermittent trouble conditions. Non-resettable regulated 24 VDC power output and RMS regulated 24 VDC output power, 2.25 amperes. 230 VAC, 50 Hz international option. 4-wire smoke detector power output. Slide-in labels for zone identification.

Code Compliance. Complies with NFPA 72 Local, Auxiliary, Remote Station, Control Station, and Proprietary Protective and Central Station Signaling Systems. Also meets NFPA13 Installation of Sprinkler Systems, NFPA15 Water Spray Fixed Systems, and NFPA16 Deluge Foam/Water and Foam-Water Spray Systems.

Optional Meters. Voltage and current meters (4XMM): The 4XMM provides a voltmeter to measure the voltage across the batteries, and an ammeter to measure the charging current to the batteries.



S6352



CS733



OV1A8.AY



419-91-E



7165-1209:19

General Specifications

Dimensions

Door: 16.125"H x 14.625"W
Backbox: 16.0"H x 14.5"W x 4.75"D
Cabinet: 16.125"H x 14.625"W x 5.375"D

Electrical Specifications

120 VAC, 60 Hz, 1.2 A

Input Terminals

14 AWG with 600 V insulation

Initiating Circuit Specifications

General

Power-limited circuitry
Operation: Style B (Class B) / Style D (Class A)

Electrical Specifications

Standby Voltage

24 VDC (ripple = 10 mV peak-to-peak), 5 mA

Alarm Current

15 mA minimum

Short Circuit Current

40 mA maximum

Maximum Detector Current In Standby

2 mA (peak) per zone

Maximum Loop Resistance

200 ohms

EOL Resistor

4.7 kohms, ½ watt

Circuit Specifications

Input Circuits

1. Detector Circuit 1/Manual Release (Style B/D)
2. Detector Circuit 2 (Style B/D)
3. Waterflow (Style B/D)
4. Supervisory (Style B/D)

Output Circuits

(optional auxiliary relays track these four circuits)

1. Alarm/Waterflow Bell (Style Y/Z)

2. Waterflow/Supervisory Bell (Style Y/Z)
3. Releasing Circuit 1 (Style Y)
4. Supervisory Bell/Release Circuit 2 (Style Y)

Front Panel Control Switches

Switch 1— Tone Silence
Switch 2— Alarm Silence
Switch 3— Alarm Activate
Switch 4— System Reset

Terminal Specifications

Four-wire Smoke Detector Power Output Maximum Current

200 mA RMS Regulated 24 VDC Power Output

Non-resettable 24 VDC Power Output Maximum DC Current

200 mA (subtracted from four-wire smoke power).

Maximum Current

0.5 A (subtracted from notification appliance power dedicated to all output circuits).

Notification/Releasing Circuit Specifications

General

Power-limited circuitry

Total Current

2.25 amps max.

Electrical Specifications

Voltage

24 VDC RMS regulated (not filtered)

Maximum Signaling Current Per Circuit

1.5 amps

Maximum Voltage Drop Due To Wiring

2 VDC

Fuses

2 AG, 4 amps

EOL Resistor

4.7 kohms, ½ watt (part no. 71252)

Field Program Selections

6-position DIP-switch To Select:

1. Two-zone, single hazard operation
2. Two-zone, single hazard operation (cross zoned)
3. Two-zone, dual hazard operation (combined release)
4. Two-zone, dual hazard operation (split release)
5. Discharge times: 0, 10, or 15 minutes

NFPA Standard Specified Requirements

Digital Communicator

NOTI•FIRE 911A

For Central Station service (NFPA 72 Central Station Protective Signaling System) or Remote Station Service (NFPA 72 Remote Station Protective Signaling System)

Transmitter Module (4XTM)

For Local Energy Municipal Box service (NFPA-72 Auxiliary Protective Signaling System):

Supervisory Current

5.0 mA

Trip Current

0.35 amps (subtracted from indicating appliance power)

Coil Voltage

3.65 VDC

Coil Resistance

14.6 ohms

Total Wire Resistance

Between Panel And Trip Coil
3 ohms

Reverse Polarity Output Voltage

24 VDC

For Remote Station Service (NFPA-72 Remote Station Protective Signaling System)

Maximum current allowed for both circuits shall not exceed 10 mA per circuit.

Optional Boards

The PDRP-1001 has mounting slots for two option boards. Any two of the three option modules may be installed.

Zone Relay Module (4XZM)

The Zone Relay module provides Form-C general alarm and trouble contacts and the following Form-C relays:

Alarm/Waterflow Bell
Waterflow/Supervisory Bell
Releasing Circuit 1
Supervisory Bell/Release Circuit 2

Dry, Form C Contacts rated for:
2.0 amps @ 30 VDC (resistive)
0.5 amps @ 30 VAC (resistive)

Relays can be silenceable/non-silenceable by jumper

Transmitter Module (4XTM)

The Transmitter module option provides a supervised output for local energy municipal box transmitter (for NFPA-72 Auxiliary Protective Signaling System) and alarm and trouble reverse polarity (for NFPA-72 Remote Station Protective Signaling System). Also included is a DISABLE switch and disable trouble LED. A jumper option allows the reverse polarity circuit to open with a System Trouble condition if no alarm condition exists.

LED Interface Module (4XLM):

The module supports the RZA-4X Remote Annunciator module. The LED Interface Module mounts to the main board occupying one of the two option connectors. Annunciator LED wiring is supervised for opens. Faults will activate System Trouble condition.

Alarm/Trouble Relays

Dry Form-C Contacts Rating

2.0 amps @ 30 VDC (resistive)
0.5 amps @ 30 VAC (resistive)

Remote Annunciator

RZA-4X

The Remote Annunciator mounts on a standard single-gang box and provides the following:
System Trouble LED (yellow)

Local Piezo Sounder
Silence Switch (for local sounder)
Alarm/Waterflow Bell LED (red)
Waterflow/Supervisory Bell LED (red)
Releasing Circuit 1 LED (red)
Supervisory Bell/Release Circuit 2 LED (red)
Note: The Remote Annunciator requires the use of an LED interface module.

System Sensor Sales and Service

System Sensor Headquarters

3825 Ohio Avenue
St. Charles, IL 60174
Ph: 800/SENSOR2
Fx: 630/377-6495
www.systemsensor.com

System Sensor Canada

Ph: 905.812.0767
Fx: 905.812.0771

System Sensor Europe

Ph: 44.1403.891920
Fx: 44.1403.891921

System Sensor in China

Ph: 86.29.8832.0119
Fx: 86.29.8832.5119

System Sensor in Singapore

Ph: 65.6273.2230
Fx: 65.6273.2610

System Sensor – Far East

Ph: 85.22.191.9003
Fx: 85.22.736.6580

System Sensor – Australia

Ph: 613.54.281.142
Fx: 613.54.281.172

System Sensor – India

Ph: 91.124.237.1770 x.2700
Fx: 91.124.237.3118

System Sensor – Russia

Ph: 70.95.937.7982
Fx: 70.95.937.7983